KSRLP963 - Compatible Dimmers

1 – low to no Audible Noise 2 – Moderate audible Noise 3- High Audible Noise Tested & Approved May 2024

Dimmer Code	Result	Observation	Acoustics	Qty	Comments
Hamilton Verve HM2031	✓	100-10% Smooth Dim, dimming below 10% can cause flicker	Acoustic rating – 1	1-10	Recommended
Enkin 250W	✓	100-10% Smooth Dim	Acoustic rating – 2	1-10	Recommended
Hamilton 741XTE	✓	100-10% Incremental Dim	Acoustic rating – 1	Up to 10	Recommended
Hamilton 741XTMSS	✓	100-10% Smooth Dim, shimmers mid- range when dimmed	Acoustic rating – 2	3-10	Recommended
Zano GRID/ZMC/ZMO150 & 250	✓	100-10% Smooth Dim, dimming below 5% can cause flicker	Acoustic rating – 1	1-10	Recommended
Newlec NL8306/12	✓	100-0% Smooth Dim, dimming below 10% can cause flicker	Acoustic rating – 1	Up to 10	Recommended
Newlec NL8806WA	✓	100-0% Smooth Dim, dimming below 10% can cause intermittent flicker	Acoustic rating – 1	Up to 10	Recommended
Newlec NL8815W	✓	100-0% Smooth Dim, dimming below 10% can cause flicker	Acoustic rating – 2	Up to 10	Recommended
Varilight V-PRO GJP100W	✓	100-0% Smooth Dim, dimming below 10% can cause intermittent flicker	Acoustic rating – 2	Up to 10	Recommended
Schneider GGBL6012LS	✓	100-10% Smooth Dim,	Acoustic rating – 1	Up to 10	Recommended
LeGrand Synergy RLCX	✓	100-0% incremental dim, dimming below 10% can cause intermittent flicker	Acoustic rating – 1	Up to 10	Recommended

PLEASE NOTE – KSR test these dimmers singularly, please consult the dimmer manufacturer for recommendations on other scenarios.
All recommendations are correct as per the date tested above, KSR cannot be held responsible for any changes in dimmer specifications.

***Acoustic Rating and dimming Conditions**

****Manufacturers recommendations may recommend using less downlights & some can be programmed for min & max parameters, please refer to any dimmer instructions included.**